## **Online Upgrade Function:**

1. If the device's firmware is old, when the device is powered on, the upgrade page is like below shows :

<b>Vi</b>		$\odot$	(B)	1×	
JF TECH	Record	Event	System	Advanced	Info
💭 Storage	Upgrade from USB				
R Account	Upgrade Position				
沢 Online User	Upgrade file			Upgrade	
∕⊪ Import/Export	Online Upgrade				
소 Upgrade	The latest version is alre	ady		Command	
AutoMaintain	Automatic upgrade	critical updates			
C Restore					
Digital					
					Cancel

• If your device has already connected to network/Or you can click the [Command] button manually, the button and the text will be changed like below shows (That means when the device connects to cloud successfully, when it is powered on, it will detect if there is new firmware in the cloud server)

JF TECH	Record	Event	System	Advanced	Info
	Record	Event	System	Advanced	Inio
💬 Storage	Upgrade from USB_				
ନ୍ Account	Upgrade Position		<b>•</b>	Linuarda	
씨 Online User				Opgrade	
/⊮ Import/Export N	Online Upgrade				
5	Has the latest firmwa	are		Upgrade	
1 Upgrade	🧾 Tips Latest upda	ates			
🖸 AutoMaintain	Automatic upgra	ade critical update	S		
C Restore					
Digital					
					Cancel

And there will be [Upgrade]button&prompt text in the version page .

JF TECH		$\bigcirc$	(B)	~		
	Record	Event	System	Advanced	Info	
[] HDD Info	Record Channel 8					
II BPS	System V4 Build Date 20	.02.R11.E15A7142.12 17-01-12 16:29:20	001.131600.00000			
C LOG	MAC 00 SerialNo b5	854c630001 36e629deedaf06				
☆ Version	Status 8					
	Nat status Co	nnected				
	Nat status code 2:"	120.92.93.27/1/+001				
	Message Has the latest firmwa	ar Upgrade				
					OK	

Click [Upgrade ]button, the device will start to upgrade the new firmwre, please do not power off &off network in the upgrade process

- If the device didn't connect to network, it won't show the above two page, online upgrade fiunction only can work in the
- 2. If you tick the "Tips Latest Updates" option before and your device has already connected to

## network

<b>W</b>	<b>&gt;&gt;&gt;</b>	$\bigcirc$	(B)	ġ.	
JF TECH	Record	Event	System	Advanced	Info
💭 Storage	Upgrade Position				
名 Account	Upgrade file		▼	Upgrade	
終 Online User	Online Upgrade				
1⊮ Import/Export	The latest version is a	Ireadv		Command	
1 Upgrade	Automatic upgrad	es le critical update	s		
AutoMaintain	Camera Upgrade				(c
C Restore	Upgrade Position		▼	Upgrade	
Digital	Upgrade file		<b>•</b>	Cancel	
					Cancel

When the device is powered on , after 1min, it will prompt there is new version firmware

Empty Password Tip > The Lastest Version	
Build Date 2018-09-20 1, add a new boot wizard 2, add a new security password function 3, modify the Hebrew character space problem	
ß	
<ul> <li>Don't display this wizard again.</li> <li>Ignore Currently Version</li> </ul>	
Upgrade Cancel	

3. "Automatic Upgrade Critial Updates" option is checked by default for special cases, such as in case of a major accident, the device networking state will force the upgrade of the server on the special version (important version) of the firmware program, usually in the early morning when the device restart will upgrade (automatic maintenance function restart or other restart).

JF TECH	Becard	Event	System	Advanced	
🛒 Storage	Upgrade from USB		oyeen		
R Account	Upgrade Position				
ନ୍ Online User	Upgrade file			Upgrade	
r⊮ Import/Export	Online Upgrade				
1 Upgrade	The latest version is already Tips Latest updates	ady	(	Command	
🔄 AutoMaintain	Automatic upgrade	critical updates			
C Restore					